

2

1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649 2650 2651 2652 2653 2654 2655 2656 2657 2658 2659 2660 2661 2662 2663 2664 2665 2666 2667 2668 2669 2670 2671 2672 2673 2674 2675 2676 2677 2678 2679 2680 2681 2682 2683 2684 2685 2686 2687 2688 2689 2690 2691 2692 2693 2694 2695 2696 2697 2698 2699 2700 2701 2702 2703 2704 2705 2706 2707 2708 2709 2710 2711 2712 2713 2714 2715 2716 2717 2718 2719 2720 2721 2722 2723 2724 2725 2726 2727 2728 2729 2730 2731 2732 2733 2734 2735 2736 2737 2738 2739 2740 2741 2742 2743 2744 2745 2746 2747 2748 2749 2750 2751 2752 2753 2754 2755 2756 2757 2758 2759 2760 2761 2762 2763 2764 2765 2766 2767 2768 2769 2770 2771 2772 2773 2774 2775 2776 2777 2778 2779 2780 2781 2782 2783 2784 2785 2786 2787 2788 2789 2790 2791 2792 2793 2794 2795 2796 2797 2798 2799 2800 2801 2802 2803 2804 2805 2806 2807 2808 2809 2810 2811 2812 2813 2814 2815 2816 2

BACKGROUND OF THE INVENTION**Field of the Invention**

0001. The invention relates generally to the field of network services. More particularly, the present invention relates to a technique for locating a point of ingress, or injection point, of a foreign, or unwanted, signal in a network. Further, by locating a point of ingress, or injection point, of a foreign signal in a network, a site of potential egress, or signal leakage, is located.

Background of the Art

0002. In the field of network services, there is much concern about both ingress of foreign signals and egress of transmission signals. Egress, or signal leakage, must be monitored and kept to a minimum to avoid interference with atmospheric signals using the same frequencies. Ingress, or interference, involves an outside signal coupled to an actual signal in the network, distorting the actual signal being transmitted. Ingress and egress can represent major costs to network operators and it is necessary to be able to locate and correct the ingress/egress point in the network in order to provide quality network communication.

0003. For example, in networks including Very high-rate Digital Subscriber Lines (VDSL) operating on twisted pair networks, interference may occur when energy from another service, such as, for example, T1 or ADSL or FCC licensed services, appears as in-band energy to the victim line. Interference may also result from distortion caused by non-linearities within a home translating energy from out-of-band signals into the VDSL band. In cable TV networks, impairments in the network such as flaws in cable

joints and connections, cracks, and loose cable shields serve as points of ingress and egress.

0004. Locating the point of ingress/egress, however, is not an easy task. Very often, the signals themselves are noise-like in nature, covering many MHz of

5 bandwidth, and thus causing difficulty in identifying the signals. One scheme suggested to assist with signal identification is the use of a distinctive signature. This suggestion, however, poses a significant disadvantage, as only part of the signal strength available in the original signal is provided by the signal bearing the distinctive signature. In addition, data-carrying capacity may be diminished if the signature is in the signaling
10 band.

0005. In the case of cable TV networks, ingress and egress have conventionally been measured using field strength meters tuned to specific channels, as allocated by the FCC, for monitoring. These meters are typically not extremely sensitive or reliable, being limited in their detector bandwidth to several kHz. Many of these meters also do
15 not permit discrimination between different foreign signals and injection points in a network. In order to discriminate, some meter systems modulate the signal in a cable with a tag, which is then demodulated and used to identify the leakage. Furthermore, the use of these systems is often time-consuming. An alternative practice is to measure ingress to a network and then selectively and systematically remove segments
20 of the network until the ingress is eliminated. This procedure necessarily involves undesirable disruption of communication over the network.

0006. It should be understood that any point where ingress occurs is a potential point of egress, and vice versa. Because it is frequently an easier task to identify ingress into

a system, the testing for egress may be prompted by monitoring ingress. Locating the source of ingress/egress often involves testing and locating the point of egress of a signal carried by the transmission cable. In locating this point, an ingress point has also been located.

- 5 **0007.** Further, it should be understood that a method and system for estimating a location of an injection point of foreign signals in a network is not limited to use with VDSL or cable TV networks, but is instead applicable to communication networks in general. As noted above, in determining an injection point of foreign signals, it is understood that a potential egress site has also been located.
- 10 **0008.** Accordingly, there is presently a need for a technique to locate the injection point of a foreign signal in a network that is sufficiently sensitive and reliable, yet is not overly time consuming and further, does not cause unnecessary disruption of communication over the network. There is also a need for a technique that has the capability to locate multiple points of ingress. Further, it is also desirable to have a
- 15 technique that permits monitoring of a network so that impairments can be identified, measured, and tracked before a communication disruption occurs.

SUMMARY OF THE INVENTION

- 0009.** The present invention comprises a method and system for estimating the location of an injection point of foreign signals in a network. Methods and systems in
- 20 accordance with the present invention estimate the location of an injection point of foreign signals by measuring samples of the signal at two locations in a network, correlating the two samples to estimate propagation delay differences between the measurement locations and the source, and using the result of the correlation to

calculate the location and magnitude of the ingress. The propagation delay, or time correlation, is proportional to the offset of the injection point from the midpoint between the measurement sites, wherein the two parameters are related by the velocity of propagation in the cable. The relative amplitude of the correlation peaks represent the

5 relative magnitude of the ingress at that location. Absolute calibration is possible by injecting a signal of known amplitude. Sensitivity can be further enhanced in methods and systems consistent with the present invention by integrating the sample correlation over time.

0010. Methods and systems consistent with the present invention may be used

10 in locating multiple points of ingress, as the resulting correlation in a system with multiple injection points would contain multiple correlation peaks, corresponding to multiple points of ingress.

0011. Methods and systems consistent with the present invention are also capable of monitoring a network for transient impairments and non-critical leakage

15 through placement of several addressable permanent or temporary frequency translators in the network that permit frequent monitoring without incurring excessive manpower.

0012. Methods and systems consistent with the present invention are capable of detecting sites of potential egress, located at the estimated injection point of a foreign

20 signal into a network.

0013. Additional advantages of the invention will be set forth in part in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The advantages of the invention will be realized

and attained by means of the elements and combinations particularly pointed out in the appended claims.

0014. It is to be understood that both the foregoing summary and the following detailed description of the invention are exemplary and explanatory only and are not
5 restrictive of the invention, as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

0015. The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate one embodiment of the invention and together with the description, serve to explain the principles of the invention. In the Figures:

10 **0016.** FIG. 1 is a schematic diagram illustrating one exemplary embodiment of the present invention;

0017. FIG. 2 is a block diagram illustrating exemplary components of one embodiment of the present invention;

15 **0018.** FIG. 3 is a flow diagram illustrating one embodiment of the method of the present invention; and

0019. FIG. 4 is a flow diagram illustrating another embodiment of the method of the present invention.

DETAILED DESCRIPTION

20 **0020.** The following description refers to the accompanying drawings. Where appropriate, the same reference numbers in different drawings refer to the same or similar elements.

0021. Referring first to FIG. 1, the method and system of the present invention may be used for any type of network system 100. A first measuring device 110

measures a first signal sample at one location along a network 105. Preferably, first measuring device 110 is physically attached to the cable. The device 110 should be tightly coupled to the transmission medium to exclude both unintended correlations of ambient signals outside the intended transmission medium and to reduce the undesired noise that might otherwise be injected into the calculations. It is possible to couple to fiber-optic cable with "clamp-on" probes that couple a small amount of energy out of the medium. Alternatively, a permanent coupler could be installed for larger signal coupling. A second measuring device 120 measures a second signal sample at a second location along the network 105. These two signal samples are correlated to obtain a propagation delay, and further obtain a distance (illustrated by the offset 150) that is proportional to the propagation delay as related by the propagation velocity of the signal. The midpoint 130 between the first measuring device 110 and the second measuring device 120 is determined. The estimated location of the injection point of a foreign signal 140 can then be determined by locating the point along the network 105 which is the distance of the offset 150 away from the midpoint 130.

0022. Referring next to FIG. 2, an alternative exemplary network system 200 is shown. A sampling device 210 includes a probe 212, a means for sending and receiving data (for example, a modem) 214, and a display unit 218, all interconnected by a link, which is preferably a fiber optic link 216. The sampling device 210 obtains a signal sample from the network 205 at the probe 212. The signal sample is then sent by the modem 214 to a node 220. The node consists of at least a means for receiving and sending data, for example, a modem, 222 and a signal processor 224. A reference signal can also be obtained at the node 220. The signal processor 224 correlates the

signal sample from the sampling device 210 and the reference signal and sends the results back to the sampling device 210. The modem 214 in the sampling device 210 receives the results and sends the results to the display unit 218. The modem 214 in the sampling device 210 and the modem 222 in the node 220 may communicate either
5 over the network 205 on an unused pair, over a telephone line (not shown), or over a wireless link (not shown).

0023. Referring to FIG. 3, a method consistent with an exemplary embodiment of this invention as illustrated in FIG. 1 is shown. First, a sample of the signal is measured by a measuring device at one point in the distribution network 310.
10 Simultaneously, a signal sample is taken by a second measuring device at a second location in a network 320. These samples are then brought to a signal processor 330 which performs a correlation calculation on the samples to determine propagation delay differences 340. The output of the signal processor is the relative correlation between the two signals containing both time and amplitude information. The correlation peaks
15 represent a map of ingress sources where the propagation delay proportionally represents the distance between the injection point and the midpoint of the cable between the two measurement sites, or the offset 350. These parameters are related by the velocity of propagation in the cable. Thus, the injection point is located a distance of offset (a function of the propagation delay, related by the velocity of
20 propagation) from the midpoint between the measurement sites 360. The amplitude of the correlation peaks represent the magnitude of the ingress at that location 370.

0024. In order to improve the sensitivity of the measurement, the output of the signal processor may be time averaged. As a further option, the correlation averaging

may be halted when no ingress signal is detected, which also leads to enhanced sensitivity.

0025. The full bandwidth of the signal is not required in order to accurately estimate the location of an injection point of foreign signals into the network, and thus the signal samples may be bandwidth limited. Increased bandwidth can result in improved spatial resolution, however.

0026. An alternate exemplary method of the present invention is described with reference to FIG. 4, consistent with an exemplary system shown in FIG. 2. A signal sample is measured at one point in a network 400 and is sent to a node 410. The node preferably includes at least a device for sending and receiving data, such as a modem, and a signal processor. At the first location, the signal sample could be measured using a device consisting of a probe and a means to send and receive data, such as a modem. A link connecting the probe and the means to send and receive data would preferably be a fiber-optic link, although other links are suitable. At the node, located at a second location in a network, a reference signal sample is also obtained 420. The reference signal sample and the signal sample sent from the device are correlated to find the propagation delay differences 340. The offset, which is a function of the propagation delay related by the velocity of propagation, is then calculated 350, and the location of the injection point is estimated as a point that is a distance of offset away from the midpoint between the node and the site where the device was used to sample the signal 360. The magnitude of the ingress may also be calculated from the amplitude of the correlation peaks 370. Finally, the processed results are sent from the node back to the device, so that the results can be displayed 430.

0027. It will be understood by those skilled in the art that various changes and modifications may be made, and equivalents may be substituted for elements thereof without departing from the true scope of the invention. In addition, many modifications may be made to adapt a particular element, technique, or implementation to the

5 teachings of the present invention without departing from the central scope of the invention. Therefore, it is intended that this invention not be limited to the particular embodiments and methods disclosed herein, but that the invention include all embodiments falling within the scope of the appended claims.